No 200:5 Pad mount C.T.s

NOTES:

① CUSTOMER TO TRENCH AND BACKFILL TO M.P. CO. SPECIFICATIONS.

② CUSTOMER TO PROVIDE AND INSTALL 3" ELECTRICAL CONDUIT AND FITTINGS FOR ALL PRIMARY CIRCUITS.

③ INSTALL LOCKS ON ALL PADMOUNTED AND METERING EQUIPMENT.

PROPOSED RAZOR-WIRE FENCE

EXISTING ROAD

6 PVC SCH 80

UE

553' 3-#2AL 12.5KV UG

ADD MP 1U3258 (TD 16510) 150 KVA PMT (TD 12210) 3Ø, 12470Y - 277/480 FOUNDATION BY CUSTOMER (TD 15036) 3-#2AL LBE (TD 15058) 3- 300:5 BMCT 2 - 288/120 PT FEEDER CIRCUIT BY CUSTOMER EMDD = 190 KVA

PROPOSED MULTI-PURPOSE BLDG EMDD = 140 KVA 165 AMPS PER Ø 3Ø - 277/480

METERING CONDUCTORS 4 - #10 CU 3 - #12 CU 1" CONDUIT (BY CUSTOMER)

METERING EQUIPMENT 1- KSWA METER 1- TEST SWITCH

RF METER

ADD MP 1U3259 (TD 16510) 225 KVA PMT (TD 12210) 3Ø, 12470Y - 277/480 FOUNDATION BY CUSTOMER (TD 15036) 6-#2AL LBE (TD 15058) 3- FAULT INDICATOR (TD 15266-1) 3- 300:5 BMCT 2 - 288/120 PT FEEDER CKT BY CUSTOMER EMDD = 200 KVA

ADD MP 1U3257 3Ø TUNC COMP. (TD 13190-1) BLOCK FOUNDATION 3- 4-WAY LB JUNCTIONS 12-#2AL LBE (TD 15058) 1- FAULT INDICATOR (TD 15266-1)

25' 20M

26' 8-#2AL 5KV UG

MATCH LINE "A" SEE SHEET # 1

160' 3-3/0 AAAC 1-#2AAAC 12.5KV

PROPOSED RAZOR-WIRE FENCE

135' 2-#2AL 12.5KV UG

230' 2-#2AL 12.5KV UG

PROPOSED RAISON INDUSTRIES INMATE EMDD = 200 KVA 140 AMPS PER Ø 3Ø - 277/480

METERING EQUIPMENT 1- KSWA METER 1- TEST SWITCH

METERING CONDUCTORS 4 - #10 CU 3 - #12 CU 1" CONDUIT

GREASE TRAP

EXISTING BUILDING

12" PVC

PATH

FENCE

SEWER LINES IN CONCRETE DRIVEWAY

M/P METER

METERING EQUIPMENT 1- TEST SWITCH 1- VM6SA METER 1- FUSE TEST PLUG 1- SOLID STATE RTU

METERING CONDUCTORS 4 - #10 CU 3 - #12 CU 1" CONDUIT (BY CUSTOMER)

RF METER

ADD MP 1U3261 (TD 16510) 300 KVA 3Ø PMT (TD 12210) (12470Y-277/480) 1- MANUAL 1- CUSTOMER (TD 15036) 3-#2AL LBE (TD 15058) 3- 400:5 BMCT 2 - 288/120 PT FEEDER CKT BY CUSTOMER EMDD = 330 KVA

PROPOSED VOCATIONAL ED BUILDING 1 EMDD = 330 KVA 397 AMPS PER Ø 3Ø - 277/480

METERING CONDUCTORS 4 - #10 CU 3 - #12 CU 1" CONDUIT (BY CUST.)

METERING EQUIPMENT 1- TEST SWITCH 1- VM6SA METER 1- MANUAL SWITCH 1- SOLID STATE RTU

1 round road cuts in place

ADD MP 1U3260 (TD 16510) 500 KVA PMT (TD 12210) 3Ø, 12470Y - 7201/208 FOUNDATION BY CUSTOMER (TD 15036) 3-#2AL LBE (TD 15058) 3-1200:5 BMCT FEEDER CT BY CUSTOMER EMDD = 420 KVA

MAIN PRISON BUILDING (EXISTING) EMDD = 420 KVA 1,167 AMPS PER Ø 3Ø - 120/208

EXISTING GARAGE

See Sheet # 1 for Service Details

LOCATION NR HUTTONSVILLE HUTTONSVILLE DISTRICT RANDOLPH COUNTY WEST VIRGINIA

Note: Second layer of razor wire to be installed May 2006

MAIN GATE

GUARD HOUSE

RF METER

3901715 3 I.D.

3313309 METER #

Read from outside 6/26/08

3201653208135-1

ADD MP 1U3262 (TD 16510) 150 KVA PMT (TD 12210) 3Ø - 12470Y - 277/480 FOUNDATION BY CUSTOMER (TD 15036) 3-#2AL LBE (TD 15038) 3- 300:5 BMCT 2 - 288/120 PT FEEDER CKT BY CUSTOMER EMDD = 175 KVA

PROPOSED STAFF BLDG EMDD = 175 KVA 211 AMPS PER Ø 3Ø - 277/480

METERING CONDUCTORS 4 - #10 CU 3 - #12 CU

METERING EQUIPMENT 1- KSWA METER 1- TEST SWITCH

ADD MP 2A9715 (TD 8732) 90'-6 (TD 6614) DADE (TD 1545) 3Ø UG TERM (TD 11510) 3- 100A I.E. CUTOUTS (6ft T FUSES) 2½" RISER SHIELD 20 M GW (TD 5361-1) 36 Guy Strain 1" x 7 Rod 6-8" Helix

PROPOSED RAZOR-WIRE FENCE

12.5KV 3-3/0 AAAC 1-#2AAAC

MATCH LINE "B" SEE SHEET # 1

FISH FARM

K Building PRISON INDUSTRIES VO-TECH

W.O. # JOB # 20-91-0195 MAP SEC # N 17-31

SUBSTATION # 20035 CIRCUIT # 01-1730

SHEET 2 OF 3 SHEETS

MONONGAHELA POWER COMPANY FAIRMONT, W. VA.

SERVICE TO HUTTONSVILLE CORRECTIONAL CENTER.

LOCATION: NR HUTTONSVILLE, WV

SCALE: 1" = 40' | P | REV.

NUMBER	RELATED DRAWINGS	NO	REVISIONS	BY	APP.	DATE	APP

	SIG.	DATE
DR.	TEP	7-8-92
TR.		
CH.		
CH.		
APP.		
APP.		
APP.		
APP.		